

CA-1250 6 Source / 12 Channels Power Amplifier

The CA-1250 is a flexible multi channel power amplifier which ideal for professional or PA. It provides 6 stereo zones, 12 channels, by Class-D digital amplifiers, more efficient operation with higher power output delivering up to 50W output power at 4 ohms or 70V/ 100V. All zones can be set to stereo or bridge mode. The output power is up to 110W at bridge mode. Beside one RCA input, an auxiliary bus input is optional for every zone. The MAP-1250 offers plenty of powerful, clean sound and reliable performance, satisfies the most discerning audio and home theater enthusiasts, simplicity of user-friendly design-all at a price that's easy to live with.



FEATURE

- * High efficiency more than 85% (class D) amplification.
- * 50W x 2 @ 4 Ohm output power per zone (25W x 2 @ 8 Ohm).
- * 4 Ohms / 70 V or 100V output selectable.
- * Stereo/ Bridge mono output.
- * Auto power off function dedicated to disable the amplifier when there is no signal from any source.
- * Wired DC Remote volume for each Zone.
- * Input level limit.
- * Power Supply: AC 115V/60 Hz or AC 230V/50Hz, can be switched.
- * LEDs for 6 ones Power On and Clip.
- * Dimension: W 430 x H 88 x D 416 mm.

SPEC

- * S/N: >85dB A WTD
- * THD: <0.1%
- * Frequency Response: 60Hz – 20K Hz
- * Input Impedance: >47K Ohm
- * Input Sensitivity: 250 mV
- * Output connection: Terminal Block